

MORSERINO NOTES (N3GE) WIFI SETUP es OPS

2/7/2021
(REV.B)

WIFI CONNECTION:

On Morserino: WiFi Functions; Config WiFi <RET>

(V3 firmware required)

On iPhone (or computer): Settings; Wi-Fi; SELECT Morserino

(5GHz WiFi not supported by Morserino)

V. 3.0

Go to Safari (web browser); use IP address: 192.168.4.1

SSID of WiFi network? _____

WiFi Password? _____

WiFi TRX Peer IP/Host? _____*

*CQ.MORSERINO.INFO = General site for QSO'S

//or/ QSOBOT.ONLINE = Programmed QSO BOT

SUBMIT

V. 4.0

Go to Safari (web browser); use IP address: 192.168.4.1

SSID of WiFi network 1? _____*

WiFi Password 1? _____*

WiFi TRX Peer IP/Host? _____*

SSID of WiFi network 1? _____*

WiFi Password 1? _____*

WiFi TRX Peer IP/Host? _____*

SSID of WiFi network 1? _____*

WiFi Password 1? _____*

WiFi TRX Peer IP/Host? _____*

*CQ.MORSERINO.INFO = General site for QSO'S

//or/ QSOBOT.ONLINE = Programmed QSO BOT

SUBMIT

(255.255.255.255=Local Broadcast IP will be used as Peer if empty)

TO SELECT A WIFI NETWORK:

On Morserino: WiFi Functions; Wifi Select

Select Wifi

Rotate **BLACK** button

Click **BLACK** button

TO SAVE CONFIGURATION:

On Morserino: Transceiver; WiFi Trx;

Double Click **BLACK** button (Set Preference)

Hold down **RED** button

STORE Snapshot 1 or 2 (Click **BLACK** button to save)

TO RECALL CONFIGURATION:

On Morserino: Transceiver; WiFi Trx;

Double Click **BLACK** button (Set Preference)

Single Click **RED** button;

RECALL Snapshot 1 or 2 (Click **BLACK** button to save)

OPERATION

CQ.MORSERINO.INFO: General site for QSO's.

On Morserino:

Transceiver; WiFi Trx; (Connecting) **<RET>**

CW **hi** response of “:hi” indicates you are online

QSOBOT.ONLINE: Programmed QSO BOT

SEE: <https://qsobot.online> Quickstart & Using QSObot

On Morserino:

Transceiver; WiFi Trx; (Connecting) **<RET>**

CW **QRL?** response of “k” indicates you are online

Start your QSO: cq cq de (callsign) (callsign) k

QSOBOT will ask questions/respond accordingly