Morserino-32 Firmware UPDATE

(W7DLR 04/07/2023)

Tip: You can update to any version, "jump" versions, OR go back to an older version.

ON COMPUTER:
Get the binary file form Morserino-32 repository on GitHub
https://github.com/oe1wkl/Morserino-32
  Go to the Software section
  Go to the Binary section
  Select the m32_v4.x.ino.wifi_lora_32-V2.bin file (4.5.2 currently)
  Click the DOWNLOAD button on the right hand side of the screen
  Open your downloads folder and verify it is there

ON MORSERINO:
  Rotate black knob to WIFI FUNCTIONS, click BLACK knob 1 time
  Rotate black knob to CHECK WIFI, click BLACK knob 1 time
  It should show the name of your WIFI and also have an IP address
                    (192.168.X.X or 10.0.X.X or similar)
      a/ IF IT DOES NOT-long press black knob to get back to main screen and follow
directions to set up M32 on your wifi. (WHITE PAPER: Morserino WIFI Setup)
      b/ If you see an IP address there, click RED button 1 time
  Rotate black knob to UPDATE FIRMWARE, click BLACK knob 1 time
  You should now see a screen like this:
    Waiting f Update
    URL: m32.local
    IP:
    192.168.X.X (or 10.0.X.X)

ON COMPUTER:
  open your web browser (Chrome, Safari, Edge, Firefox, etc)

 In the address bar type in the IP address shown on M32 screen
      It should open a login page

At M32 Firmware Update Login Page: USERNAME **m32** PASSWORD **update**   *Login*

On m32.local web page: Choose file; SELECT from DOWNLOADS M32 . . .bin   *Begin*

(NEVER UPLOAD MP3 FILE, ONLY .bin)

ON MORSERINO: **WILL RESTART & SHOW NEW VERSION**